

KS-858E LCD Intelligent Alarm System

(CE Approval, ISO9001 quality system)



Main Function And Characteristics

- * 16-zone (8 wireless and 8 wired) with 4*4 keyboard and lattice LCD display.
- * Voice pre-recorded.
- * 8 partitions can be programmed independently. 8 remote controllers and 8 users code can be programmed for 8 partition to ARM/DISARM independently.
- * Support to ADEMCO CONTACT ID and Ks6+2 monitoring center communication protocol
- * Access codes, 1 installer code, 1 master code, 8 common user code and duress code.
- * Dial 5 telephone numbers (mobile and pager number). Dialing type (tone or pulse) and appointed communication zone can be programmed. Alarm telephone is priority.
- * Option for ARM/DISARM and system status report or not.;
- * Phone line cut or short-circuit will send an alarm. (indicator or siren for optional)
- * Remote Arm, Disarm, monitor, and on-site alarm setup.
- * Automatically register between Wireless PIR detector, remote controller and main console (8 wireless can up to 24 zones, and 8 remote controllers)
- * Wired zone responds speed (5ms-1000ms) and support (Normal Open, Normal Close and end- of-line resistance) at freedom.
- * Zone attribute can be program for fire alarm, medical alarm, emergency Alarm at freedom. Each zone can be programmed with different remote controllers.
- * Two timers can be set to Arm/Disarm independently.
- * Alarm delay (00-99 seconds) and Arm delay (00-99 seconds) can be set for appointed zones.
- * Main unit disassembly, slave detector disassembly, AC power cut, backup battery lower and slave detector power lower will activate alarm.
- * Work with wired/wireless Siren and linkage device.
- * Lastest 30 pieces alarm (Month/Day/hour/minute) can be recorded and can't be deleted. Last Arm /Disarm time can be remembered.
- * Main unit and wireless PIR detector make communication times in 26 hour to check if there is communication malfunction. If there is a malfunction, the main console will alert corresponding zone within 26 hours.
- * Slave detector sends report to main unit for on/off. The report will be remembered in record.
- * Both AC220V and 12V, 7AH rechargeable battery power supplied. And change automatically. The backup battery can work 24 hours or more in standby.
- * Battery lower power alert and discharge protection
- * Telephone lightningproof.